

# FWT-201

## Surge protector wall tap with dimmable nightlight



This wall tap is designed to plug in two devices in one location, providing surge protection for two outlets. A built-in nightlight with photosensor and touch dimmer automatically turns on after dark to provide dusk-to-dawn illumination. This low-profile power multiplier is easy to install and fits into tight spaces. Perfect for home and office applications.

### Highlights

- Wall-mount AC power protection for two electronic components
- Surge protection rating of 1080 joules
- Surge protection indicator lights
- Overload and short circuit protection
- Dimmable nightlight with touch sensor



Dimmable  
nightlight



2 Protected  
outlets

LEVEL

2

Breaker

+

Surge  
Protector

**MPN****FWT-201**

<b>Input</b>	
Voltage	110/220VAC
Amps	10A
Frequency	50/60Hz (autosensing)
Watts	1250W
Surge rating	300J
Maximum spike current	6500A
AC plug style	NEMA 5-15P
<b>Output</b>	
Outlets	Two NEMA 5-15R
Overload Protection	Included
<b>Physical appearance</b>	
Nightlight	Included with touch sensor and dimmer
Housing	Flame retardant plastic
Color	White
Dimensions	2.8x2.7x1.3in
Weight	0.2lb
<b>Additional information</b>	
Warranty	Lifetime

