

PC CASE MAG PANO M100R PZ / WHITE A NEW TURNING POINT





SPECIFICATIONS

MAG PANO M100R PZ / WHITE
Micro- ATX Tower
M-ATX(Back-connect supported) / ITX
1 x USB 3.2 Gen 1 Type-A 1 x USB 3.2 Gen 2x2 Type-C 1 x Audio-Out / Mic-in 1 x LED Switch Button 1 x Power Button
1 x 2.5" 1 x 2.5"/3.5" combo (up to 2 x 2.5" or 1 x 2.5"+ 1 x 3.5")
5
390 mm / 15.35 inches *Support horizontal installation only.
175 mm / 6.9 inches
ATX
200 mm / 7.87 inches
Top: 3 x 120 mm / 2 x 140 mm Front: NA Rear: 1 x 120 mm / 1 x 140 mm Side: 3 x 120 mm Bottom: 1 x 120 mm PSU Shroud: 2 x 120 mm
Side: 3 x 120 mm Rear: 1 x 120 mm
Side: 3 x ARGB Fan (Reverse-blade) Rear: 1 x ARGB Fan
Top: 120 / 240 / 360 mm Front: NA Rear: 120 / 140 mm Side: NA Bottom: NA
440 x 235 x 405 mm / 17.32 x 9.25 x 15.94 inches
8.66 kg
11.29 kg

CONNECTIONS

FEATURES



Pre-build with Reverse-blade Fan Pre-installed on the side are reverse blade fans, allowing the

Pre-installed on the side are reverse blade fans, allowing the unobstructed display of the ARGB fan's beauty without any interference from fan frames.



Supporting back-connect motherboards enables easy installation without the worry of forgetting to connect cables, which might otherwise require disassembling graphics cards and coolers.

270-degree Panoramic Display



Drawing inspiration from the MAG logo, create a distinctive chassis design that embodies the unique MAG characteristics. The front interior of the chassis incorporates a space for displaying figurines, complemented by a 270-degree panoramic tempered glass, transforming it into a showcase-style chassis.

GPU Support Stand



Equipped with a level indicator to ensure effortless adjustment of the support height during installation, preventing sagging. Meanwhile, its magnetic base secures more stability within the chassis.

1 to 4 ARGB-FAN Control Board

This fan control board supports up to 4 x ARGB fan function. Allow you to use the LED switch button to adjust the ARGB lighting intuitionally.



A NEW TURNING POINT



- 1. 1x USB 3.2 Gen 2x2 Type-C
- 2. 1x USB 3.2 Gen 1 Type-A
- 3. Mic In/ Audio Out
- 4. LED Switch Button