forzaups.com



## NT-511-511D

Forza's NT series is designed to provide electric protection for your personal computer and peripherals.



With its compact size, the unit is ideal for small work spaces at the office or at home. Although small in size, it provides the maximum protection against the constant threat of electrical supply outages.

## **Highlights**

- Uninterruptible power system
- Power protection for home and office equipment
- Boost and buck AVR to stabilize voltage
- 6 outlets with battery back up and AVR protection
- Phone, fax & modem protection (RJ-11)
- Three-year warranty





🕂 Breaker + Surge Protector + Voltage Protector + Voltage Regulator

- + Power Back up

MPN	NT-511	NT-511D	
General			
Capacity	500VA/250W		
Input			
Nominal voltage	120V		
Voltage range	78-145VAC		
Frequency	45-65Hz (autosensing)	40Hz - ∞ (autosensing)	
AC plug style	NEMA 5-15P		
Dutput			
Nominal voltage	120V +/- 10%	120V +/- 10%	
Frequency	50/60Hz		
Frequency stability	+/- 1Hz battery mode		
Waveform	Modified sine wave		
Total outlets	6 (NEMA 5-15R)		
Full battery / Surge protection outlets	4		
Surge protection only outlet	2		
Phone/modem/fax protection	RJ-11		
Battery			
Battery type and quantity	12V 4.5Ah (1)		
Backup time	18 min*		
Recharge time	6 hours to 90% after complete discharge		
Voltage regulation			
Voltage regulation (120/220V)	120V		
Boost feature (120/220V)	Vin x 1.18		
Buck feature (120/220V)	Vin x 0.85		
Frequency regulation			
Automatic frequency selection	Yes		
Line/Battery transfer			
Typical transfer time	2-4ms		
Low line transfer to battery (120/220V)	78VAC		
High line transfer to battery (120/220V)	145VAC		
Alarms/Indicators			
Visual indicators	AC mode: solid blue		
	Battery mode: flashing blue		
	Fault mode: blue light goes out		
Audible	Battery mode: sounds every 10 seconds		
	-	Low battery: sounds every second	
	Overload: sounds every 0.	Overload: sounds every 0.5 second	
	Fault: continuous sound		
Protection			
Full protection	Line mode: 110%+20%/-10%; shutdown after 5 minutes and go to		
		fault mode. 120%+20%/-10%; shutdown immediately and go to fault mode. Battery mode:120%+20%/-10%; shutdown immediately	
Joules	mode. Battery mode: 120%+20%-10%; 200J	shutdown immediately	
Special features	2003		
"Cold start" option	Yes		
Auto charge	Yes		
Environment	105	Yes	
Operating temperature	32-104° F		
Storage temperature	5-113°F		
Relative humidity			
Audible noise	0-90% non-condensing <40 dB at one meter		

MPN	NT-511	NT-511D
Physical appearance		
Power switch	Yes (lighted)	
Housing	Flame retardant plastic	
Color	Black	
Cord length	3ft	
Dimensions	11x4x5.6in	
Weight	10.lb	
Additional information		
Warranty	3 years**	

\* Calculated with a single PC plus monitor \*\* Limited to 2 years on batteries



Forza Power Technologies<sup>®</sup> is a registered trademark. Other company and product names mentioned herein are trademarks of their respective owners. Mention of third-party products is for informational purposes only and constitutes neither an endorsement nor a recommendation. Forza Power Technologies<sup>™</sup> assumes no responsibility with regards to the performance or use of these products. Made in China.